

Ins a1

Description

FIELD OF THE INVENTION

The present invention pertains to low power and high speed integrated circuits in the compound semiconductor field utilizing field effect transistors and more specifically complementary field effect transistors used in concert including enhancement mode self-aligned metal-oxide-compound semiconductor transistors and depletion mode self-aligned metal-oxide-compound semiconductor transistors and methods of materials growth and fabrication of said structures and the ultra large scale integration of said transistors.

BACKGROUND OF THE INVENTION

The gallium arsenide and indium phosphide integrated circuit industry has been limited without a technology that simultaneously allows the integration of complementary field effect transistor devices and transistors with low gate leakage currents. In contrast to silicon technology that has a very mature and useful complementary metal oxide semiconductor (CMOS) technology. Field effect transistor (FETs) widely used in the III-V semiconductor industry employ metal gates and Schottky gate contacts that have quiescent-state leakage currents exceeding many microamps. The use of metal gates in compound semiconductor technology further results in individual transistors and integrated circuits that have excessively high power dissipation, reduced transconductance, reduced logic swing and the inability to operate on a single power supply, and generally limited performance characteristics. The high magnitude of the quiescent leakage current limits the maximum integration of GaAs devices to circuits of several hundred thousand transistors for those skilled in the art. In contrast, the simultaneous integration of many millions of transistors is possible at high integration densities using silicon CMOS technology. These ultra high integration densities and levels cannot be obtained using metal, Schottky-style gates that are not insulated in compound semiconductor FETs. Thus Si CMOS technology offers significant advantages in terms of individual gate leakage, circuit integration level and cost.

However when compared to silicon, complementary GaAs and InP circuit technology exhibits faster and more optimized speed/power performance and efficiency at a low supply voltage of 1V and below. The market acceptance of these GaAs and InP integrated circuit technologies remains low because of the lack of ability to demonstrate high integration densities with low amounts of operating power. Thus, silicon CMOS dominates the field of digital integrated circuitry and neither GaAs nor InP technologies can successfully penetrate this market.

What is needed are new and improved compound semiconductor field effect transistors (FET). What is also needed are new and improved compound semiconductor FETs using metal-oxide-semiconductor junctions (MOSFET). What is also needed are new and improved compound semiconductor MOSFETs using a self-aligned gate structure. What is also needed are new and improved self-aligned compound semiconductor MOSFETs using enhancement mode and depletion mode operation. What is also needed are new and improved self-aligned compound semiconductor MOSFETs with stable and reliable device operation. What is also needed are new and improved self-aligned compound semiconductor MOSFETs which enable optimum compound semiconductor device performance. What is also needed are new and improved self-aligned compound semiconductor MOSFETs with optimum efficiency and output power for RF and microwave applications. What is also needed are new and improved self-aligned compound semiconductor MOSFETs for use in complementary circuits and architectures. What is also needed are new and improved self-aligned compound semiconductor MOSFETs for low power/high performance complementary circuits and architectures. What is also needed are new and improved self-aligned compound semiconductor MOSFETs which offer the design flexibility of complementary architectures. What is also needed are new and improved self-aligned compound semiconductor MOSFETs which keep interconnection delays in ultra large scale integration under control. What is needed are new and useful complementary integrated circuits where each individual transistor has a leakage current approaching 10^{-12} amp. What is needed is a truly useful integrated circuit technology for GaAs and InP that allows for the useful and economical operation of ULSI digital integrated circuits in compound semiconductors. What is needed are new and improved compound semiconductor MOSFET integrated circuits with very low net power dissipation. What is needed are new and improved compound semiconductor MOSFET devices with low gate leakage currents that may be integrated together to form ultra large

scale integrated circuits that include millions of transistors. What is needed are new and improved complementary MOSFET devices and circuits in compound semiconductors that allow the direct use, transfer and application of silicon CMOS design that already exists in the art.

What is also needed are new and improved methods of fabrication of self-aligned compound semiconductor MOSFETs. What is also needed is new and improved methods of fabrication of self-aligned compound semiconductor MOSFETs which are compatible with established complementary GaAs heterostructure FETs technologies. What is also needed are new and improved compound semiconductor MOSFETs which are relatively easy to fabricate and use.

BRIEF DESCRIPTION OF THE DRAWINGS

A more complete understanding of the present invention may be derived by referring to the detailed description and claims when considered in connection with the figures, wherein like reference numbers refer to similar items throughout the figures, and:

FIG. 1 is simplified cross sectional view of a self-aligned enhancement mode compound semiconductor MOSFET in accordance with a preferred embodiment of the present invention;

FIG. 2 is a simplified flow chart illustrating a method of manufacturing a self-aligned enhancement mode compound semiconductor MOSFET in accordance with a preferred embodiment of the present invention.

The exemplification set out herein illustrates a preferred embodiment of the invention in one form thereof, and such exemplification is not intended to be construed as limiting in any manner.

DETAILED DESCRIPTION OF THE DRAWINGS

The present invention provides, among other things, a self-aligned enhancement mode metal-oxide-compound semiconductor FET. The FET includes a gallium oxygen insulating structure that is composed of at least two distinct layers. The first layer is most preferably more than 10 angstroms thick but less than 25 angstroms in thickness and composed substantially of gallium oxygen compounds including but not limited to stoichiometric Ga_2O_3 and Ga_2O , and possibly a lesser fraction of other gallium oxygen compounds. The upper insulating layer in the gallium oxide insulating structure is composed of an insulator that does not intermix with the underlying gallium oxygen insulating structure. This upper layer must possess excellent insulating qualities, and is most typically composed of gallium oxygen and a third rare earth element that together form a ternary insulating material. Therefore the entire gallium oxide rare earth gate insulator structure is composed of at least two layers and may contain a third intermediate graded layers that consists of a mixture of the upper insulating material and the gallium oxygen compounds that compose the initial layer. Together the initial gallium oxygen layer, any intermediate graded layer and the top insulating region form both a gallium oxide insulating structure and the gate insulator region of a metal-oxide-compound semiconductor field effect transistor. The initial substantially gallium oxygen layer forms an atomically abrupt interface with the top layer of the compound semiconductor wafer structure, and does not introduce midgap surface states into the compound semiconductor material. A refractory metal gate electrode is preferably positioned on the upper surface of the gate insulator structure layer. The refractory metal is stable on the gate insulator structure layer at elevated temperature. Self-aligned source and drain areas, and source and drain contacts are positioned on the source and drain areas. In all embodiments preferred and otherwise, the metal-oxide-compound semiconductor transistor includes multi-layer gate insulator structure including an initial gallium oxygen layer, intermediate transition layer, and upper insulating layer of 30-250 angstroms in thickness positioned on upper surface of a compound semiconductor heterostructure that form the gate insulator structure. The preferred embodiment also comprises a compound semiconductor heterostructure including a GaAs, $\text{Al}_x\text{Ga}_{1-x}\text{As}$ and $\text{In}_y\text{Ga}_{1-y}\text{As}$ layers with or without n-type and/or p-type charge supplying layers which are grown on a compound semiconductor substrate, a refractory metal gate of W, WN, or WSi, self aligned donor (n-channel FET) or acceptor (p-channel FET) implants, and source and drain ohmic contacts. In another preferred embodiment, the compound semiconductor heterostructure comprises an $\text{In}_y\text{Ga}_{1-y}\text{As}$, $\text{Al}_x\text{In}_{1-x}\text{As}$, and InP compound semiconductor heterostructure and n-type and/or p-type charge supplying layers which are grown on an InP substrate, and a refractory metal gate of W, WN,

etched until oxide layer 31 is exposed using a refractory metal etching technique such as a fluorine based dry etching process. The refractory metal etching procedure does not etch the oxide layer 31, thus, oxide layer 31 functions as an etch stop layer such that upper surface of top layer 15 remains protected by oxide layer 31. All processing steps are performed using low damage plasma processing. Self-aligned source and drain areas 21 and 22, respectively are realized by ion implantation of Si (n-channel device) and Be/F or C/F (p-channel device) using the refractory metal gate electrode 17 and the dielectric spacers 26 as implantation masks. Such ion implantation schemes are compatible with standard processing of complementary compound semiconductor heterostructure FET technologies and are well known to those skilled in the art. The implants are activated at 700-900°C using rapid thermal annealing in an ultra high vacuum environment such that degradation of the interface 16 established between top layer 15 and oxide layer 31 is completely excluded. Finally, ohmic source and drain contacts 19 and 20 are deposited on the self-aligned source and drain areas 21 and 22, respectively. The devices may then be interconnected using the standard methods to those skilled in the art of integrated microelectronics and integrated circuit manufacture.

FIG. 2 is a simplified flow chart illustrating a method of manufacturing a self-aligned enhancement mode compound semiconductor MOSFET in accordance with a preferred embodiment of the present invention. In step 102, a compound semiconductor wafer structure is produced using standard epitaxial growth methods in the art. In step 103, a layer consisting of gallium oxygen compounds including but not limited to Ga_2O_3 and Ga_2O is deposited on upper surface of said compound semiconductor wafer structure. In step 104, an insulating layer of gallium oxygen and one or more rare earth elements is deposited on the upper surface of the initial gallium oxygen compound layer. The gallium oxide gate insulator structure is formed in steps 104 and 105. In step 106, a stable refractory gate metal is positioned on upper surface of said gate insulator structure. In step 108, source and drain ion implants are provided self-aligned to the gate electrode. In step 110, source and drain ohmic contacts are positioned on ion implanted source and drain areas.

In a preferred embodiment, step 100 provides a compound semiconductor substrate such as GaAs or InP. Step 102 includes the preparation and epitaxial growth of an atomically ordered and chemically clean upper surface of the compound semiconductor wafer structure. Step 103 preferably comprises thermal evaporation from a purified and crystalline gadolinium gallium garnet or Ga_2O_3 source on an atomically ordered and chemically clean upper surface of the compound semiconductor wafer structure. Step 104 comprises the formation of a gallium+oxygen+rare earth elemental insulating layer formed through the simultaneous vacuum evaporation of gallium oxygen species and at least one rare earth element such as Gadolinium with the simultaneous oxidation using the effluent of an oxygen gas plasma source directed in simultaneous combination with other thermal evaporation sources toward substrate 100. The initial gallium oxygen compound layer of the gate insulator structure preferably functions as an etch stop layer such that the upper surface of the compound semiconductor wafer structure remains protected by the gate oxide during and after gate metal etching. The refractory gate metal desirably does not react with or diffuse into the gate oxide layer during high temperature annealing of the self-aligned source and drain ion implants. The quality of the interface formed by the gate oxide layer and the upper surface of the compound semiconductor structure is desirably preserved during high temperature annealing of the self-aligned source and drain ion implants. The self-aligned source and drain implants are desirably annealed at approximately 700°C in an ultra high vacuum environment. The self-aligned source and drain implants are desirably realized by positioning dielectric spacers on the sidewalls of the refractory gate metal.

Thus, new and improved compound semiconductor devices and methods of fabrication are disclosed. The new and improved self-aligned enhancement mode metal-oxide-compound semiconductor heterostructure field effect transistors enable stable and reliable device operation, provide optimum compound semiconductor device performance for low power/high performance complementary circuits and architectures, keep interconnection delay in ULSI under control, and provide optimum efficiency and output power for RF and microwave applications as well as for digital integrated circuits that require very high integration densities.

These improvements essentially solve or overcome the problems of the prior art, such as high gate leakage in compound semiconductor FET devices, low integration densities, dc electrical instability, and electrical hysteresis, and therefore provide a highly useful invention. While we have shown and described specific embodiments of the present invention, further modifications and improvements will occur to those skilled in the art. We desire it to be

[illegible]